

# Gland with press system

## Your benefits


Time saving of up to 85%

Simple and very fast assembly

Sizes: M12-M50


Protection rating IP68

VDE and UL approved



### 1. Plug-in

Plug-in the cable gland onto the assembly tool (hand tool, electrical, pneumatic).



### 2. Insert and clamp

Insert the cable gland through the hole and clamp into position.



### 3. Done!

After clamping, retract tool from the cable gland. Done in no time!



Wall thickness 1.00-2.50 mm

p/n light grey	p/n silver grey	p/n black	Size	Cable clamping range (mm)	Hole	p/u
18028000	18028001	18028002	M12	4,0 - 6,5	12,4 +/- 0,3	50
18028003	18028004	18028005	M16	6,0 - 9,5	16,4 +/- 0,3	50
18028006	18028007	18028008	M20	7,0 - 12,0	20,4 +/- 0,3	50
18028009	18028010	18028011	M25	11,0 - 16,0	25,4 +/- 0,3	25
18028012	18028013	18028014	M32	14,0 - 21,0	32,4 +/- 0,3	25
18028015	18028016	18028017	M40*	19,0 - 27,5	40,4 +/- 0,3	10
18028018	18028019	18028020	M50*	26,0 - 34,0	50,4 +/- 0,3	10

\*M40 for wall thickness 1,00 - 5,50 mm (not UL and VDE approved)

\*M50 for wall thickness 1,00 - 4,00 mm (not UL and VDE approved)

## Gland with press system

Wall thickness 2,50 - 4,00 mm

p/n light grey	p/n silver grey	p/n black	Size	Cable clamping range (mm)	Hole	p/u
18028021	18028022	18028023	M12	4,0 - 6,5	12,4 +/- 0,3	50
18028024	18028025	18028026	M16	6,0 - 9,5	16,4 +/- 0,3	50
18028027	18028028	18028029	M20	7,0 - 12,0	20,4 +/- 0,3	50
18028030	18028031	18028032	M25	11,0 - 16,0	25,4 +/- 0,3	25
18028037	18028034	18028035	M32*	14,0 - 21,0	32,4 +/- 0,3	25

\*M32 for wall thickness 2,50 - 5,50 mm

Wall thickness 4,00 - 5,50 mm

p/n light grey	p/n silver grey	p/n black	Size	Cable clamping range (mm)	Hole	p/u
18028036	18028037	18028038	M16	6,0 - 9,5	16,4 +/- 0,3	50
18028039	18028040	18028041	M20	7,0 - 12,0	20,4 +/- 0,3	50

Wall thickness 5,50 - 7,00 mm

p/n light grey	p/n silver grey	p/n black	Size	Cable clamping range (mm)	Hole	p/u
18028042	18028043	18028044	M16	6,0 - 9,5	16,4 +/- 0,3	50

# Gland with press system

## Tooling

p/n	Description	PU
16000900	Hand tool	1
16000901	Electrical tool	1
16000902	Spare battery	1
16000903	Pneumatic tool	1

## Tooling

p/n	Description	PU
16000904	M12 insert	1
16000905	M16 insert	1
16000905	M20 insert	1
16000907	M25 insert	1
16000908	M32 insert	1
16000909	M40 insert	1
16000910	M50 insert	1