








Valve Connectors

Adapter bases for DIN Valve connectors - Form A - EN175301-803 (DIN43650)



| Technical drawing | | | | | | | | | | | |
|---|--|---------|---|--|------------|--|--|------------|---|--|--|
|  | | |   | | |   | | |   | | |
| Product description | | | | | | | | | | | |
| Connector type | Adapter base for DIN valve connectors | | | Adapter base for DIN valve connectors | | | Adapter base for DIN valve connectors | | | | |
| Conforms to | EN175301-803 | | | EN175301-803 | | | EN175301-803 | | | | |
| Construction type | A | | | A | | | A | | | | |
| Description | Square Angled 90° adapter AG1 series | | | Square Angled 90° adapter AG1 series | | | Square Angled 90° adapter AG1 series | | | | |
| Contacts spacing | 18mm | | | 18mm | | | 18mm | | | | |
| Number of contacts | 2poles + 2P.E. | | | 2poles + 2P.E. | | | 2poles + 2P.E. | | | | |
| Earth positioning | H.6-12 | | | H.6-12 | | | H.6-12 | | | | |
| Adapter colour | Black | | | Black | | | Black | | | | |
| Adapter height | 33.2mm | | | 33.2mm | | | 33.2mm | | | | |
| Technical data | | | | | | | | | | | |
| Rated voltage | 24V DC | 115V DC | 230V DC | 24V AC/DC | 115V AC/DC | 230V AC/DC | 24V AC/DC | 115V AC/DC | 230V AC/DC | | |
| Circuit type | Led + Diode(1A) | | | Bipolar Led + Varistor | | | Bipolar Led + RC circuit | | | | |
| Led colour | Red | | | Red | | | Red | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| | | | | | | | | | | | |
| Packaging | | | | | | | | | | | |
| Qty/Bag | 1pc / bag | | | 1pc / bag | | | 1pc / bag | | | | |
| Other accessories options | | | | | | | | | | | |
| - | | | | | | | | | | | |
| Notes: | | | | | | | | | | | |
| | Adapter available with different led colour. Adapter available with different circuits. | | | Adapter available with different led colour. Adapter available with different circuits. | | | Adapter available with different led colour. Adapter available with different circuits. | | | | |